

## 35. Any speaker does not work

### INSPECTION PROCEDURE

1 Is radio operating normally?

YES

CD auto changer faulty.

NO

2 Is hiss noise produced by non-functioning speaker.

YES

Radio assembly faulty.  
Recheck system after repair.

NO

3 Does continuity exist in speaker wire harness?

NO

Speaker wire harness faulty.

YES

4 Temporarily install another speaker. Function OK?

YES

Speaker faulty.

NO

Radio assembly faulty.  
Recheck system after repair.