

DTC	B1232 / 32	Jam protection pulse switch circuit on driver door
------------	-------------------	---

DTC	B1234 / 34	Jam protection pulse switch circuit on passenger door
------------	-------------------	--

DTC	B1236 / 36	Jam protection pulse switch circuit on rear right door
------------	-------------------	---

DTC	B1238 / 38	Jam protection pulse switch circuit on rear left door
------------	-------------------	--

CIRCUIT DESCRIPTION

These DTCs are output when a malfunction of pulse switch within power window motor is detected.

DTC No.	DTC Detecting Condition	Trouble Area
B1232/32	No change in pulse switch more than 2.0 seconds even if opening glass down when limit switch is OFF (window glass is fully closed).	<ul style="list-style-type: none"> • Jam protection pulse switch • Wireharness
B1234/34		
B1236/36		
B1238/38		

HINT:

Please refer to power window control system of BE section for switch inspection, and to each door system of DI section for wireharness inspection.