

DIAGNOSTIC TROUBLE CODE CHART

If a DTC is displayed during the DTC check, check the circuit listed in the table below and proceed to the page given.

DTC No. (See Page)	Detection Item	Trouble Area	MIL *	Memory
P0500 (DI-319)	Vehicle Speed Sensor Malfunction	<ul style="list-style-type: none"> • Open or short in No.1 vehicle speed sensor circuit • No.1 vehicle speed sensor • Combination meter • ECM 	●	○
P0750 (DI-320)	Shift Solenoid "A" Malfunction (Shift Solenoid Valve No.1)	<ul style="list-style-type: none"> • Shift solenoid valve No.1 is stuck open or closed • Valve body is blocked up or stuck 	●	○
P0753 (DI-321)	Shift Solenoid "A" Electrical Malfunction (Shift Solenoid Valve No.1)	<ul style="list-style-type: none"> • Open or short in shift solenoid valve No.1 circuit • Shift solenoid valve No.1 • ECM 	●	○
P0755 (DI-320)	Shift Solenoid "B" Malfunction (Shift Solenoid Valve No.2)	<ul style="list-style-type: none"> • Shift solenoid valve No.2 is stuck open or closed • Valve body is blocked up or stuck 	●	○
P0758 (DI-321)	Shift Solenoid "B" Electrical Malfunction (Shift Solenoid Valve No.2)	<ul style="list-style-type: none"> • Open or short in shift solenoid valve No.2 circuit • Shift solenoid valve No.2 • ECM 	●	○
P0770 (DI-325)	Shift Solenoid "E" Malfunction (Shift Solenoid Valve SL)	<ul style="list-style-type: none"> • Shift solenoid valve SL is stuck open or closed • Valve body is blocked up or stuck • Lock-up clutch 	●	○
P0773 (DI-327)	Shift Solenoid "E" Electrical Malfunction (Shift Solenoid Valve SL)	<ul style="list-style-type: none"> • Open or short in shift solenoid valve SL circuit • Shift solenoid valve SL • ECM 	●	○
P1520 (DI-330)	Stop Light Switch Signal Malfunction	<ul style="list-style-type: none"> • Short in stop light switch signal circuit • Stop light switch • ECM 	●	○
P1700 (DI-331)	Speed Sensor No.2 Circuit Malfunction (No.2 Vehicle Speed Sensor)	<ul style="list-style-type: none"> • Open or short in No.2 vehicle speed sensor circuit • No.2 vehicle speed sensor • ECM 	●	○
P1780 (DI-335)	Park/Neutral Position Switch Malfunction	<ul style="list-style-type: none"> • Short in park/neutral position switch circuit • Park/neutral position switch • ECM 	●	○

*: ●... MIL lights up